



KONICA MINOLTA

Auto Scan Spectrophotometer **FD-9**

Easy-to-use, accurate and super fast!
Automatic next-generation chart reader



Main Specifications of FD-9

Illumination/viewing system	45°a: 0°(annular illumination)* ¹ Conforms to CIE No. 15, ISO 7724/1, DIN5033 Teil 7, ASTM E 1164, and JIS Z 8722 Condition a for reflectance measurements.
Spectral separation device	Concave grating
Wavelength range	380 to 730 nm
Wavelength pitch	10 nm
Half bandwidth	Approx. 10 nm
Measurement area	Approx. ø3 mm
Light source	LED
Measurement range	Spectral reflectance: 0 to 150% Colorimetric: Within $\sigma\Delta E_{00}$ 0.05
Repeatability	* Under Konica Minolta standard conditions where a white calibration plate is measured 30 times at 10-second intervals after white calibration has been performed
Inter-instrument agreement	Within ΔE_{00} 0.3 (Average of 12 BCRA Series II color tiles compared to values measured with a master body under Konica Minolta standard conditions)
Measurement time	Approx. 4 min per 1,500 patches * Konica Minolta standard conditions* ³
Output item	Spectral reflectance
Measurement conditions* ²	M0 (A), M1 (D50) , M2 (A + UV-cut filter), C, ID50, D65, ID65, F2, F6, F7, F8, F9, F10, F11, F12, User-defined illuminant
Backing condition	White backing, compliant with ISO13655
Interface	USB2.0, 100Base-TX
Power	AC adapter
Size (W × D × H)	FD-9 only : 716 x 251 x 159 mm Auto Sheet Feeder : 601 x 1,158 (when tray is open) x 245 mm FD-9 mounted on Auto Sheet Feeder : 716 x 1,158 x 256 mm
Weight	FD-9 only: Approx. 10.5 kg FD-9 mounted on Auto Sheet Feeder: Approx. 28.5 kg
Operation temperature/humidity range	10 to 35°C, 30 to 85% relative humidity with no condensation
Storage temperature/humidity range	0 to 45°C, 0 to 85% relative humidity with no condensation

Measurable Chart Specifications*⁴

Width	45 to 330 mm
Length	170 to 1,500 mm
Thickness	0.05 to 0.45 mm
Smallest patch size	6×6 mm
Maximum patches per sheet	1,394 (A4) 2,928 (A3)
Margins(minimum)	Leading: 23 mm; Trailing: 33 mm; Left/right sides: 4 mm each

Main Specifications of FD-S2w

Operating environment	OS	Windows® 7 Professional 64 bit (x64) Windows® 8.1 Pro 64 bit (x64) Windows® 10 Pro 64 bit (x64) OS X® 10.9 to 10.11 mac OS™ 10.12 to 10.14
	CPU	1 GHz or faster processor
	Memory	2 GB or more (64 bit)
	Hard disk	At least 8 GB of available disk space
	Display	Display unit capable of showing at least 1,024 x 768 dots
Compatible Instruments	Interface	USB 2.0* ⁵ , 100BaseTx
	FD-9 FD-7/CL-500A (Readout only for user-defined light source)	
Features	Chart creation, chart measurement, measurement data display, measurement file output, QR code creation	
Displayed measurement data	Spectral reflectance, colorimetric value, density	
Measurement conditions* ²	M0 (A), M1 (D50) , M2 (A + UV-cut filter), C, ID50, D65, ID65, F2, F6, F7, F8, F9, F10, F11, F12, User-defined illuminant	
Illuminant	A, C, D50, ID50, D65, ID65, F2, F6, F7, F8, F9, F10, F11, F12, A + UV filter, User-defined light source, Auto* ⁶	
Observer	2° or 10° Standard Observer	
Color space	L*a*b*, L*C*h, XYZ	
PC supported languages	English, French, German, Spanish, Japanese, Chinese (Simplified)	
Output format	CxF3: ISO17972-1:2015 CGATS: ISO28178:2009 (ANSI CGATS-17) FD-S2w original format (csv/txt)	

*¹ Illumination for wavelengths under 400 nm is unidirectional.

*² M0, M1 and M2 are lighting conditions contained in ISO13655 4.2.2 Illumination requirements and measurement conditions.

*³ Chart size: A3, Patch size: 6 x 6 mm, Patch layout: 32 rows x 47 columns

*⁴ Even if paper size is within the ranges specified, some charts may not be measured.

*⁵ Ethernet connection is recommended on OS X® 10.11. Communication error may occur when using USB connection.

*⁶ The illuminant is automatically set according to the selected measurement condition.

- Windows® is a trademark or registered trademark of Microsoft Corporation in the USA and other countries.
- Displays shown are for illustration purpose only.
- The specifications and appearance shown herein are subject to change without notice.
- KONICA MINOLTA, the Konica Minolta logo and symbol mark, and "Giving Shape to ideas" are registered trademarks or trademarks of KONICA MINOLTA, INC.
- Other company names and product names used herein are trademarks or registered trademarks of their respective companies.

SAFETY PRECAUTIONS

For correct use and for your safety, be sure to read the instruction manual before using the instrument.

- Be sure to use the specified power supply voltage. Improper connection may cause a fire or electric shock.

ISO Certifications of KONICA MINOLTA, Inc., Sakai Site

JQA-QMA15888
Design, development, manufacture/
manufacturing management, calibration,
and service of measuring instruments

JQA-E-80027
Design, development,
manufacture, service and sales
of measuring instruments

KONICA MINOLTA, INC.
Konica Minolta Sensing Americas, Inc.
Konica Minolta Sensing Europe B.V.

Osaka, Japan
 New Jersey, U.S.A.
 European Headquarter /BENELUX
 German Office
 French Office
 UK Office
 Italian Office
 Swiss Office
 Nordic Office
 Polish Office
 Turkish Office
 SE Sales Division
 Beijing Office
 Guangzhou Office
 Chongqing Office
 Qingdao Office
 Wuhan Office

Konica Minolta (CHINA) Investment Ltd.

Konica Minolta Sensing Singapore Pte Ltd.
Konica Minolta Sensing Korea Co., Ltd.

Addresses and telephone/fax numbers are subject to change without notice. For the latest contact information, please refer to the KONICA MINOLTA Worldwide Offices web page :

©2015 KONICA MINOLTA, INC.

Phone : 888-473-2656 (in USA), 201-236-4300 (outside USA)
Phone : +31 (0) 30 248-1193
Phone : +49 (0) 89 4357 156 0
Phone : +33 (0) 1 80 11 10 70
Phone : +44 (0) 1925 467300
Phone : +39 02849488.00
Phone : +41 (0) 43 322-9800
Phone : +46 (0) 31 7099464
Phone : +48 (0) 71 73452-11
Phone : +90 (0) 216-528 56 56
Phone : +86- (0) 21-5489 0202
Phone : +86- (0) 10-8522 1551
Phone : +86- (0) 20-3826 4220
Phone : +86- (0) 23-6773 4988
Phone : +86- (0) 532-8079 1871
Phone : +86- (0) 27-8544 9942
Phone : +65 6563-5533
Phone : +82 (0) 2-523-9726

Fax : 201-785-2482
Fax : +31 (0) 30 24 81 211
Fax : +49 (0) 89 4357 156 99
Fax : +33 (0) 1 80 11 10 82
Fax : +44 (0) 1925 711143
Fax : +39 02849488.30
Fax : +41 (0) 43 322-9809
Fax : +48 (0) 71 734 52 10
Fax : +90 (0) 212-253 49 69
Fax : +86- (0) 21-5489 0005
Fax : +86- (0) 10-8522 1241
Fax : +86- (0) 20-3826 4223
Fax : +86- (0) 23-6773 4799
Fax : +86- (0) 532-8079 1873
Fax : +86- (0) 27-8544 9991
Fax : +65 6560-9721
Fax : +82 (0) 31-995-6511

<https://konicaminolta.com/instruments/network>

9242-A8AN-41 CABPK00